

More Distance, Louder and Clearer Audio – Reliable Radio Communication Tool



- 5 W output power plus new antenna provides 1.5 times*¹ more communication distance
- 1500 mW powerful audio and 1.5 times*² higher sound pressure
- Dust-protection, water resistance and a tough body (IP54 and MIL-STD 810G)
- 19 hours*³ of long lasting battery life
- 200 channels with 5-character alphanumeric display
- Automatic DTMF transmission linked to PTT (on pressing PTT (Log-in) / on releasing PTT (Log-off))
- Durable BNC type antenna connector

And More

- The rotary knob on the top panel is assignable either to volume control or channel selector
- Supplied BC-240, battery charger with a charging control function that prolongs the life of the battery
- Integrated VOX function
- Built-in CTCSS and DTCS encoder/decoder
- Priority, memory, skip and tone scanning

*¹ Wide open space. Approximate, comparing the IC-G86 with the IC-G80. Communication range may differ depending on operating environment or weather conditions, etc.

*² Approximate, comparing the IC-G86 with the IC-G80.

*³ At EX Hi Power mode. TX : RX : standby = 5 : 5 : 90 (The Power Save function is on.)



1500 mW powerful audio

SPECIFICATIONS

GENERAL	
Frequency range	136-174 MHz
Type of emissions	F2D, F3E (FM, FM-N)
Number of channels	200 channels
Antenna impedance	50 Ω
Power supply requirement	7.5 V DC
Operating temperature range	-20°C to +60°C, -4°F to +140°F
Frequency stability	±2.5 ppm (-20°C to +60°C, -4°F to +140°F)
Current drain	
TX (EX Hi/Hi/Mid/Low)	1.6/1.4/1.0/0.5 A
RX (Max. audio)	450 mA typ. (INT SP), 200 mA typ. (EXT SP)
Dimensions (WxHxD) (Projections not included)	58.6 × 112 × 30.5 mm, 2.3 × 4.4 × 1.2 in (with BP-298)
Weight (Approximate)	300 g, 10.6 oz (with BP-298, FA-B57V)
TRANSMITTER	
Output power	5.0/3.0/2.0/0.5 W (EX Hi/Hi/Mid/Low)
Maximum frequency deviation	±5.0 kHz/±2.5 kHz (Wide/Narrow)
Spurious emissions	-80 dB
External microphone connector	3-conductor 2.5 (d) mm (1/10")/2.2 kΩ
RECEIVER	
Sensitivity	0.14μV (at 12dB sinad)
Squelch sensitivity	0.11μV
Selectivity (Wide/Narrow)	75 dB/70 dB
Intermodulation	70 dB
Audio output power	
Internal speaker	1500 mW (with 8 Ω load)
External speaker	550 mW (with 8 Ω load)
External speaker connector	3-conductor 3.5 (d) mm (1/8")/ 8 Ω

All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810G	
	Method	Procedure
Low Pressure	500.5	I, II
High Temperature	501.5	I, II
Low Temperature	502.5	I, II
Temperature Shock	503.5	I-C
Solar Radiation	505.5	I
Rain Blowing/Drip	506.5	I, III
Humidity	507.5	II
Salt Fog	509.5	-
Dust Blowing	510.5	I
Vibration	514.6	I
Shock	516.6	I, IV

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Ingress Protection Standard

Dust and Water	IP54 (Dust-protection, water resistance)
----------------	--

Supplied accessories :

- BP-298, battery pack
- BC-240, desktop charger
- BC-242, AC adapter
- MB-124, belt clip
- FA-B57V, antenna

OPTIONS

BATTERY PACKS & CASE

Battery pack type	Capacity	Operating time*
BP-298 Rechargeable Li-ion	2100 mAh (min.), 2250 mAh (typ.)	Up to 19 hours
BP-299 Rechargeable Li-ion	3050 mAh (min.), 3150 mAh (typ.)	Up to 27 hours
BP-263 AA (LR6) batteries × 6	—	—

* At EX Hi Power mode. TX : RX : standby = 5 : 5 : 90 (The Power Save function is on.)

RAPID CHARGERS

BC-240 Rapid charger for BP-298/BP-299
BC-191 Rapid charger for BP-264

PTT SWITCH CABLE & PLUG ADAPTER CABLE VS-4LA
 For manual PTT operation
OPC-2004LA
 For VOX operation

MULTI-CHARGER
BC-214N* For BP-298/BP-299

SPEAKER-MICROPHONES

Waterproof

*The AD-139/AD-120 charger adapters are supplied with the BC-214N/BC-197, depending on the charger version.

EARPHONE-MICROPHONES

HM-166LA

CHARGER BRACKET MB-130
 For single chargers

CIGARETTE LIGHTER CABLE CP-23L
 For single chargers

DC POWER CABLES

OPC-515L
 For single chargers

OPC-656
 For multi-chargers

ANTENNAS

FA-B45V 140 MHz
FA-B57V 160 MHz

BELT CLIP MB-124

PROGRAMMING SOFTWARE & CABLES

CS-G86 Programming software
OPC-478UC Handheld to PC USB cable
OPC-474 Handheld to handheld

The "3D GENUINE Icom label" is attached to the rear chassis under the battery. check the Icom website for details: <http://www.icom.jp/world/genuine-info/>



Icom, Icom Inc. and Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. All trademarks are the properties of their respective holders.

Icom Inc. 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 www.icom.co.jp/world **Count on us!**

Icom America Inc.
 12421 Wilows Road NE,
 Kirkland, WA 98034, U.S.A.
 Phone: +1 (425) 454-8155
 Fax: +1 (425) 454-1509
 E-mail: sales@icomamerica.com
 URL: <http://www.icomamerica.com>

Icom (Europe) GmbH
 Communication Equipment
 Auf der Krautweide 24
 65812 Bad Soden am Taunus, Germany
 Phone: +49 (6196) 76885-0
 Fax: +49 (6196) 76885-50
 E-mail: info@icom-europe.com
 URL: <http://www.icomeurope.com>

Icom France s.a.s.
 Zac de la Plaine,
 1 Rue Brindejone des Moulins, BP 45804,
 31505 Toulouse Cedex 5, France
 Phone: +33 (5) 61 36 03 03
 Fax: +33 (5) 61 36 03 00
 E-mail: icom@icom-france.com
 URL: <http://www.icom-france.com>

Asia Icom Inc.
 6F No. 68, Sec. 1 Cheng-Teh Road,
 Taipei, Taiwan, R.O.C.
 Phone: +886 (02) 2559 1899
 Fax: +886 (02) 2559 1874
 E-mail: sales@asia-icom.com
 URL: <http://www.asia-icom.com>

Your local distributor/dealer:

บริษัท ซี.ซี.มอนเรดิโอ จำกัด
 14/48-49 อาคารโครงการคาสเตด บางนา
 หมู่ที่ 15 ตำบลบางแก้ว อำเภอบางพลี
 จังหวัดสมุทรปราการ 10540
 โทร. 02 090 2920-22 , 0816439181
 แฟกซ์. 02 090 2922
 Email : info@gsimon.com

Icom Canada
 Glenwood Centre #150-6165
 Highway 17A, Delta, B.C.,
 V4K 5B8, Canada
 Phone: +1 (604) 952-4266
 Fax: +1 (604) 952-0090
 E-mail: info@icomcanada.com
 URL: <http://www.icomcanada.com>

Icom Spain S.L.
 Ctra. Rubi, No. 88 "Edificio Can Castanyer"
 Bajos A 08174, Sant Cugat del Valles,
 Barcelona, Spain
 Phone: +34 (93) 590 26 70
 Fax: +34 (93) 589 04 46
 E-mail: icom@icomspain.com
 URL: <http://www.icomspain.com>

Icom (Australia) Pty. Ltd.
 Unit 1 / 103 Garden Road,
 Clayton, VIC 3168 Australia
 Phone: +61 (03) 9549 7500
 Fax: +61 (03) 9549 7505
 E-mail: sales@icom.net.au
 URL: <http://www.icom.net.au>

Shanghai Icom Ltd.
 No.101, Building 9, Caifuxingyuan Park,
 No.188 Maoting Road, Chedun Town,
 Songjiang District, Shanghai, 201611, China
 Phone: +86 (021) 6153 2768
 Fax: +86 (021) 5765 9987
 E-mail: bjicom@bjicom.com
 URL: <http://www.bjicom.com>

Icom Brazil
 Rua Itororó, 444 Padre Eustáquio
 Belo Horizonte MG,
 CEP: 30720-450, Brazil
 Phone: +55 (31) 3582 8847
 Fax: +55 (31) 3582 8987
 E-mail: sales@icombrasil.com

Icom (UK) Ltd.
 Blacksole House, Altira Park,
 Herne Bay, Kent, CT6 6GZ, U.K.
 Phone: +44 (0) 1227 741741
 Fax: +44 (0) 1227 741742
 E-mail: info@icomuk.co.uk
 URL: <http://www.icomuk.co.uk>

Icom New Zealand
 39C Rennie Drive, Airport Oaks,
 Auckland, New Zealand
 Phone: +64 (09) 274 4062
 Fax: +64 (09) 274 4708
 E-mail: inquiries@icom.co.nz
 URL: <http://www.icom.co.nz>